



MECO supports
Bureau
of Energy Efficiency
(BEE), Govt. of
India's mission
to institutionalize
certification of
Electric / Electronic
goods for ECOMARK
under
Gazette of India

PHA 5850



Under BEE's PAT Scheme (Perform, Achieves & Trade) it is mandated to compulsorily improve their Energy Efficiency by adopting all the available measures including replacement of their old Equipments with New and Energy Efficient Equipments

Versatile Handy instrument using micro controller technology and easy to use software program for recording and downloading.

Useful for time to time monitoring of Power Parameters, Energy and Presence of Harmonics at several Location / Machines.

Cost Effective & Efficient Tool for Energy Auditor, Maintenance Persons, Service Providers, Site / Plant Engineers.

MECO Power and Harmonics Analyser Model PHA-5850 can Analyze, Measure, Monitor & Data Log values of Power Quality & Consumption (Energy). Capable of analyzing IT standby power consumption to the maximum demand of factory. It comes with a user friendly application software that increases the utility & performance of this instrument. The analyzer is ideal for an any Engineer/ Inspector for carrying out Periodic Visits, Maintanance of Plant, Vigilance checks, Surveys and Energy Audits for checking at Industrial and Consumers end.

Features :

- Analysis of 3P4W, 3P3W, 1P2W, 1P3W Systems
- Display of 35 Parameters in one screen (3P4W)
- Programmable CT (1 to 600) and PT (1 to 3000) Ratios
- Graphic Phasor Diagram
- RMS, PEAK Value & Crest Factor
- True RMS value, Active Power, Apparent & Reactive Power (KVA, KVAR)
- Power Factor, Phase Angle (Φ) & Energy (WH, KWH, KVARH, PFH)
- Average / Maximum Demand (KW, MW, KVA, MVA) with Programmable Period
- Analysis of Total Harmonic Distortion (THD-F)

- Display of 50 Harmonics in one Screen with Wave form with Peak value (1024 Sample / Period)
- Capture 28 Transient Events with Programmable Threshold (%) (DIP, SWELL & OUTAGE)
- Built in timer & Calendar for Data Logging
- Facility to retrieve Power Data & Harmonics on Meter Screen
- 512K Memory with Programmable Interval (2 to 3000 seconds, 17000 records for 3P4W System)
- Optical Isolated RS-232C~USB Interface
- Software for easy download of Recorded Data & Transient events
- Calculated Unbalanced Current through Neutral line

General Specification : PHA5850

Power	Eight x 1.5V "AA" Batteries	Overload Indication	OL
External DC Input	Power supply adapter 12 Volts. DC	Operating Condition	-10°C to 50°C \leq 85% RH
Display	Dot Matrix LCD (240x128) with backlight	Storage Condition	-20°C to 60°C \leq 75% RH
LCD Update Rate	1 time / second	Dimensions	257 x 155 x 57 mm
Power Consumption	140mA (approx.)	Weight	1160 g (Batteries included)
No. Of Samples	1024 samples / period	Accessories	Voltage Test Leads x 4 (3 meter long)
Data Logging Files	85		Alligator Clips (Voltage) x 4 (R.Y.B.N.)
Max. File Capacity	17474 records (3P4W, 3P3W)		Carrying Bag x1
	26210 records (1P3W)		Batteries 1.5V x8
	52420 records (1P2W)		External DC Adaptor x1
	4096 records (50 Harmonics / record)		Software CD x1
Sampling Time	2 to 3000 seconds for data logging		Users Manual x1
Low battery Indication	B		Software Manual x1
			Optical USB Cable x1
			Current Clamps x 3 (Any One CT Set)

Specifications : (23°C ± 5°C)

AC Current

(50Hz or 60Hz, Auto Range, True RMS, Crest Factor <4, CT=1)

Model : PHA-5850A (100A) (Overload Protection AC 200A)

Range	Resolution	Accuracy of Readings
0.04 - 1A	0.1mA / 1mA	± 0.5% ± 0.05A
0.4 - 10A	0.001A / 0.01A	± 0.5% ± 0.05A
4 - 100A	0.01A / 0.1A	± 1.0% ± 0.5A

Model : PHA-5850B (1000A) (Overload Protection AC 2000A)

Range	Resolution	Accuracy of Readings
10.00A	0.001A / 0.01A	-
5A - 100.0A	0.01A / 0.1A	± 0.5% ± 0.5A
50A - 1000.0A	0.1A / 1A	± 0.5% ± 5A

Model : PHA-5850C (3000A) (Overload Protection AC 3000A)

Range	Resolution	Accuracy of Readings
10.0 - 300.0A	0.01A / 0.1A	± 1% of range
300.0 - 3000A	0.1A / 1A	

Model : PHA-5850D (1200A) (Overload Protection AC 1200A)

Range	Resolution	Accuracy of Readings
6.0 - 120.0A	0.01A / 0.1A	± 1% of range
120.0 - 1200A	0.1A / 1A	

Harmonic of AC Voltage in Percentage

Range	Resolution	Accuracy
1 - 20th	0.1%	± 2%
21 - 49th		± 4% of reading ± 2.0%
50 - 99th		± 6% of reading ± 2.0%

Harmonic of AC Current in Percentage

Model : PHA-5850A (100A)

Range	Resolution	Accuracy
1 - 10th	0.1%	± 0.2% of reading ± 1%
11 - 20th		± 2% of reading ± 1%
21 - 50th (A range)		± 5% of reading ± 1%
21 - 50th (mA range)		± 10% of reading ± 1%
51 - 99th		± 35% of reading ± 1%

Model : PHA-5850B (1000A)

Range	Resolution	Accuracy
1 - 20th	0.1%	±2%
21 - 49th		± 4% of reading ± 2.0%
50 - 99th		± 6% of reading ± 2.0%

Model : PHA-5850C (3000A) & PHA-5850D (1200A)

Range	Resolution	Accuracy
1 - 20th	0.1%	±2 %
21 - 50th		± 6%
51 - 99th		± 10%

AC Watt

(50Hz or 60Hz, PF 0.5~1, CT=1, continuous waveform)

Model : PHA-5850A (100A)

Range (0 to 100A)	Resolution	Accuracy of Readings
5.0 - 999.9W	0.1W	± 1% ± 0.8W
1.000 - 9.999KW	0.001KW	± 1% ± 8W
10.00 - 99.99KW	0.01KW	± 1% ± 80W
100.0 - 999.9KW	0.1KW	± 1% ± 0.8KW
1000 - 9999KW	1KW	± 1% ± 8KW

Model : PHA-5850B (1000A)

Range (0 to 1000A)	Resolution	Accuracy of Readings
5.0 - 999.9W	0.1W	± 1% ± 0.8W
1.000 - 9.999KW	0.001KW	± 1% ± 8W
10.00 - 99.99KW	0.01KW	± 1% ± 80W
100.0 - 999.9KW	0.1KW	± 1% ± 0.8KW
1000 - 9999KW	1KW	± 1% ± 8KW
0.000 - 9.999MW	0.001MW	± 1% ± 80KW

Model : PHA-5850C (3000A)

Model : PHA-5850D (1200A)

Range (0 to 3000A or 0 to 1200A)	Resolution	Accuracy of Readings	
		>20V & >30A	<20V or <30A
10.0 - 999.9W	0.1W	± 1% of range	± 2% of range
1.000 - 9.999KW	0.001KW		
10.00 - 99.99KW	0.01KW		
100.0 - 999.9KW	0.1KW		
1000 - 9999KW	1KW		

AC Voltage

(50Hz or 60Hz, Auto Range, True RMS, Crest Factor <4, Input Impedance 10MΩ, VT (PT) = 1, Overload Protection AC 800V)

Range	Resolution	Accuracy of Readings
20.0V - 500.0V (Phase to Neutral)	0.1V	± 0.5% ± 5dgts
20.0V - 600.0V (Phase to Phase)		

Power Factor (PF)

Model : PHA-5850A (100A) & PHA-5850B (1000A)

Range	Resolution	Accuracy
0.00 - 1.00	0.01	± 0.04

Model : PHA-5850C (3000A) & PHA-5850D (1200A)

Range	Resolution	Accuracy	
		>20V & >30A	<20V or <30A
0.000 - 1.000	0.001	± 0.04	± 0.1

