

# India's First ...

# MECO®



Model 9A09



## Dual Channel 60000 Count DMM

- ◆ 0.02% DC & 0.1% AC (Basic Accuracy)
- ◆ 60000 Counts Resolution
- ◆ 200 KHz (max.) Bandwidth
- ◆ TRMS with fast ACV/ACA Response
- ◆ Dual Channel Measurement similar to Dual Channel DSO (V+V, V+A)
- ◆ Hz+Duty Cycle Dual Display
- ◆ RS-232 ASCII interface
- ◆ Data Logging  
(Model 9A09-DL with 10708 Records)
- ◆ Capacitance Measurement
- ◆ User Interface Software

On display at  
**ELECRAMA 2004**  
HALL 5, STALL F-4

## 80000 Count TRMS DMM with Function Generator and 10 Digit Counter

- ◆ Dual-Display : Primary 80000, Secondary 80000
- ◆ 0.05% DC (Basic Accuracy)
- ◆ More than 50 Functions
- ◆ Frequency Measurement from 0.5Hz to 1000.000000MHz
- ◆ 16 Frequency points, 1% to 99% Duty Selectable  
Square Wave Output
- ◆ Resistance 0.1Ohm to 80MOhm, 10MOhm to 8000MOhm
- ◆ Capacitance 1pF to 100uF
- ◆ Temperature -50°C to 1372°C, -58°F to 2502°F
- ◆ dBm 20 types of reference impedance
- ◆ Auto Data Hold / Peak Hold
- ◆ 36Hrs Dynamic Recording MAX / MIN / AVG / MAX-MIN
- ◆ RS-232 Isolated Optical Interface
- ◆ Timer, Back Light, Auto Power Off



Model 81K

## MECO INSTRUMENTS PRIVATE LTD.

PO BOX 6388, 301, Bharat Industrial Estate, TJ Road, Sewree (W), Mumbai - 400015

Tel : 91-22-24137253, 24137423, 24132435  
Fax : 91-22-24146234  
E-mail : sales@meconst.com  
Website : www.meconst.com